

AUTOMATIC VOLTAGE REGULATOR (STABILIZER)

Power Star Australian Series (3-steps Regulation)



- › Provide stable output voltage through boost and buck stabilizer
- › Built-in thermal switch for over-temperature protection
- › Provide modem / phone line surge protection
- › Provide overload & short circuit protection
- › Coaxial cable line protection (Optional)
- › 5VDC USB charging port (Optional)
- › User-friendly visual LED indicators
- › Anti-flammable plastic housing
- › Accept wide input range
- › Wall mounting holes
- › Child protector
- › Cable collector

MODEL	PSE-800A	PSE-1200A	PSE-2000A
CAPACITY	800VA/400W	1200VA/600W	2000VA/1000W
INPUT			
Voltage	220/230/240Vac		
Voltage Range	161-288Vac		
Frequency	50/60Hz		
OUTPUT			
Steps of Regulation	3-steps(2-steps boost & 1-step buck)		
Output Receptacles	Australian: 3pcs AVR regulated & surge protected + 3pcs surge protected only		
Protection	Network surge suppression: RJ-45		
	Overload / short circuit: Manual reset circuit switch		
	Over-temperature: Thermal switch		
INDICATORS			
Power On/Off LED	Green		
Boost LED	Yellow		
Buck LED	Yellow		
ENVIRONMENT			
Humidity	0-95%(Non-condensing)		
Noise Level	Less than 40dB at 1M		
PHYSICAL			
Dimension	263*120*85mm		
Net Weight	1.6kgs	2.0kgs	2.3kgs

*Product specifications are subject to change without further notice.