

AUTOMATIC VOLTAGE REGULATOR (STABILIZER)

Power Star Series (2-steps Regulation/Tower Type)



- › 5VDC USB charging ports 2.4A max. for iPhone / iPad / smartphones
- › Provide stable output voltage through boost and buck stabilizer
- › Eight output receptacles Nema5-15R or Universal Nema type
- › Built-in thermal switch for over-temperature protection
- › Provide overload and short circuit protection
- › Fire retardant plastic material

MODEL	I-332U-600	I-332U-800	I-332U-1000
CAPACITY	600VA/300W	800VA/400W	1000VA/500W
INPUT			
Voltage	110/115/120Vac or 220Vac		
Voltage Range	110Vac: 88-136Vac ; 115Vac: 92-142Vac 120Vac: 96-148Vac ; 220Vac:176-272Vac		
Frequency Range	50/60Hz		
OUTPUT			
Steps of Regulation	2-steps (1-step Boost & 1-step Buck)		
Output Receptacles	Nema5-15R or Universal Nema: 4pcs AVR regulated plus surge protected + 4pcs surge protected only		
5VDC USB Charging Port	2 ports 2.4A max.		
Protection	Overload / short circuit: Manual reset circuit switch		
	Over-temperature: Thermal switch		
	Surge protection: 175 Joules		
INDICATORS			
Power On/Off LED	Green		
Boost LED	Yellow		
Buck LED	Yellow		
ENVIRONMENT			
Humidity	0-95%(Non-condensing)		
Noise Level	Less than 40dB at 1M		
PHYSICAL			
Dimension(W*D*H)	107*107*153mm		

*Product specifications are subject to change without further notice.